



Palm Tungsten E2

Lifecycle phase: **Mature**. Release: April 2005. [About Lifecycles](#).
[Change Product](#)

[Home](#) [Learn](#) [Downloads](#) [Solutions](#) [Support Services](#) [Community](#)

[Print Version](#) [Get Palm Desktop 6.2](#)


Palm Wi-Fi Card Drivers for Palm OS

Download & Install:

[Windows](#)

[Mac](#)

Article ID: 15202



Description & Features

- [Important prerequisites & system requirements](#)
- [Fatal Alerts](#)
- [User Guide](#)



No drivers needed for Treo 700w smartphone:

These drivers are for Palm OS devices only. If you have a Windows Mobile device such as the Treo 700w smartphone, you do not need this software download. The Wi-Fi Card drivers are already included on the Treo 700w smartphone.

Important prerequisites & system requirements

- **Tungsten E2, Tungsten T3, Tungsten T5, or a Zire 72 device.** The Wi-Fi Card driver does not support other devices. If you have a Treo 700w smartphone, you do not need to install drivers for the Wi-Fi Card; this software is built into in your smartphone.
- Palm Wi-Fi Card inserted during the installation process
- **5 MB of free memory on your device** to accommodate the installer. *The 5MB is needed only temporarily.* When complete, the installer will automatically be deleted. The driver software takes up approximately **1.1MB** of space after installation.
- Battery fully charged.
- **If your battery is not full or you do not have 5 MB of free memory, do NOT install** the Wi-Fi Card software onto your handheld.
- PC running Windows 98/NT 4.0/2000/Me/XP
- Or -
- Mac OS 9.2.2, Mac OS X, version 10.1.2 or higher
- Network HotSync supported on Windows only

Fatal Alerts

I am receiving Fatal Alerts after I installed the Wi-Fi software, or when selecting or editing a Wi-Fi Network.

If you went through the software installation and are receiving Fatal Alerts when selecting or editing a Wi-Fi network, you may need to reinstall the palmOne Wi-Fi Card software. Before reinstalling the Wi-Fi software, you will need to Hard Reset your handheld.

NOTE: When you perform a hard reset, all records and entries stored in your handheld are erased. Formats, preferences and other settings are restored to their factory default settings.

Download & Install

Windows

Download

palmOneWiFiCard_v1_2.zip (3.8MB)

[End User License Agreement](#)

1. Change all conduits to 'Synchronize the files' This ensures a current backup of data normally backed up during a HotSync operation.
2. Download palmOneWiFiCard_v1_2.zip (3.8 MB ZIP file)
3. Extract all the files using a standard unzip utility. Note the location of the directory/folder the file is extracted to.
4. Double click to open the palmOneWiFiCard_v1_2 folder.
5. Double click the palmOneWi-FiCardDriver.exe file to launch the installation.
6. Choose your setup language from the menu shown and click Next.
7. The Wi-Fi Card InstallShield Wizard will appear, make sure you have 5 MB of free memory on your handheld and click Next.
8. Review the Wi-Fi Card Installation Instructions and click Next.
9. Review the palmOne License Agreement and click Yes.
10. Select the User Name for the handheld to which you want to install the Wi-Fi Card Software from the drop down list and then click Next.
11. Setup is now ready to install the Wi-Fi Card Software for your handheld.
12. Place your device in the cradle and HotSync your handheld to your computer. The Wi-FiInstaller will be installed to your handheld.
13. Follow the instructions on your handheld to complete the installation.

Mac

Download

palmOneWiFiCard_v1_2.sit (2.2MB)

[End User License Agreement](#)

1. Change all conduits to 'Synchronize the files'. This ensures a current backup of data normally backed up during a HotSync operation.
2. Download palmOneWiFiCard_v1_2.sit(2.2 MB SIT file)
3. Your browser should automatically download the file and you will see the .sit file appear on the desktop (or your default download folder.)
4. Double click the downloaded file (palmOneWiFiCard_v1_2.sit) to extract the compressed files.
5. Double click to open the palmOneWiFiCard_v1_2 folder.
6. Double click on the WiFi Installer1.2.prc file. The file should show up in the install screen.
7. In the "Install Handheld files" screen select the desired user from the drop down menu.
8. Place your handheld in the cradle and HotSync your handheld to your computer, the WiFiInstaller will be installed to your handheld.
9. Follow the instructions on your handheld to complete the installation.

User Guide

Palm OS

Windows Mobile

[English](#) (PDF: 683KB / 78
pages)

[English](#)

Treo 700w information posted January 5, 2006

Tungsten E2 driver support posted May 12, 2005

Tungsten T3, Tungsten T5, and Zire 72 version posted November 29, 2004

Was this helpful?

yes • no

Article ID:

15202

Relevant Products: Palm Wi-Fi Card